

PROHDMISP12 & PROHDMISP14 2 & 4-Way HDMI Splitter

PROception

The splitter allows one HDMI device to be split easily to multiple HDMI displays, e.g. TV, monitor, projector, etc. The splitter can also be placed at the end of a long cable to regenerate the HDMI signal.



Kit Contents:

- HDMI splitter.
- Power adapter.
- User manual.

Instructions:

Device is not "hot swappable" always disconnect power before inserting or removing any cable.

1. Connect a HDMI cable from the device's HDMI output into the HDMI splitter's input.
2. Connect a HDMI cable from the splitter's output to the displayer's HDMI input.
3. Repeat step 2. for the number of displays required.
4. Connect the 5V power supply to the HDMI splitter.

Features:

- Support HDMI 1.4b.
- Support Full 3D.
- Support HDCP 1.4.
- Support HDMI resolution up to 3840x2160/30Hz.
- Support the max baud rate of 3.4G and max bandwidth of 340MHz.
- Support deep color 8/10/12bit.
- Support input up to 8m AWG26 HDMI standard cable length, output up to 8m AWG26 HDMI standard cable length.
- Displays single source, multi-output high-definition signal source from DVD player A / V receiver, set-top box.
- 5V power adapter.

Specifications:

HDMI version	HDMI 1.4b
HDMI resolution	UP TO 3840*2160/30Hz
Support video color format	8/ 10/12bit deep color
Support audio format	DTS-HD/Dolby-trueHD/DTS/Dolby-AC3/DSD
Max bandwidth	340MHz
Max baud rate	3.4Gbps
Input cable distance	≤8m AWG26 HDMI standard cable
Output cable distance	≤8m AWG26 HDMI standard cable
HDMI input	1 HDMI
HDMI output	2 HDMI
Max working current	500mA
Specifications of power adapter	Input: AC (50HZ, 60HZ) 100V-240V; output: DC5V
Operating Temperature range	(-15 to +55℃)
Operating Humidity range	5 to 90%RH (No Condensation)
Dimension (L x W x H)	103x42x16mm
Weight	100g